



## USB 2.0 LAN Dock

Model No. : LD201, LD202



LD201

LD202



### Features

- Add one high-speed serial port, one printer port, one PS/2 keyboard & mouse, 3 USB2.0 High Speed downstream ports and one Ethernet port to your PC or notebook in seconds.
- Improve the inconvenience of configuring old PC solutions like card extension solutions, which require adjusting IRQ or jumper settings and the incompatibility of various brands of docking solutions or bus repeaters.
- Avoid the hassle of removing your PC case, or rebooting the operating system during installation.
- Built-in 10/100Mbps Fast-Ethernet and IEEE802.3x flow control functions for 100BASE-TX and 10BASE-T.
- Complies with USB specifications 2.0 (and under), with IEEE802.3u 100BASE-TX and with IEEE802.3 10BASE-T standards.

### Specifications

Dimensions (LXWXH)	120 x 65 x 26mm
Unit Weight	130g
Cable Length	USB A/B type cable 1.8M
Connect Ports	USB, RJ45, PS/2, RS-232 and Printer
USB Upstream port	X 1
USB Downstream port	USB 2.0 x 3
Ethernet port	10/100M x 1
Mini PS/2 port	X 2 (Keyboard, Mouse)
RS-232 port (DB-9)	X 1
IEEE-1284 Printer port (DB-25)	X 1
Compliant with USB version	USB 1.0/USB 1.1/USB 2.0
Compliant with HID version	USB HID 1.1
Complies IEEE802.3/IEEE802.3u	Yes
Auto-Negotiation for 10M/100M	Yes
Over-Current protection	Yes
Bus-Power limit current protection	500mA (When external adaptor applied)
Power & Access LED indicator	Yes
Power	By host or external adaptor
Power Adaptor	DC 5V/2A (Optional)
OS Complies	Windows 98/98SE/ME/2000/XP